

## DA-1000

### One Channel Class D Amplifier

- 1000 Watt
- 100V / 8 Ohm Connection Option
- Rack Type Design
- Protection, Clip, Signal LEDs

**EN 54 16**



### Technical Specifications

|                                  |                                          |
|----------------------------------|------------------------------------------|
| Output Power                     | 1000W                                    |
| Speaker Output                   | 100V / 8 Ohm                             |
| Frequency Response               | 20Hz-20kHz                               |
| Input                            | 0.775V, 0dBu, balanced phoenix connector |
| Input Impedance                  | 10 Kohm                                  |
| Total Harmonic Distortion(T.H.D) | <0.1% (1kHz/-3dB,100W)                   |
| S/N Ratio                        | >80dB                                    |
| Crosstalk                        | >60dB, 1kHz, max output                  |
| Power Consumption                | 600 Watt                                 |
| Operating Voltage                | AC 110-230V, 50-60Hz                     |
| Dimensions                       | 482 × 420 × 44mm                         |
| Weight                           | 5.5 Kg                                   |